

Suprathreshold stochastic resonance: suppression of noise by strong periodic signals

Andrey L. Pankratov

*Dipartimento di Scienze Fisiche "E.R.Caianiello", Universita' di Salerno, Italy
and Institute for Physics of Microstructures of RAS, Nizhny Novgorod, RUSSIA.
E-mail: alp@ipm.sci-nnov.ru.*

We consider an overdamped Brownian motion in "quartic" potential subjected to periodic driving. This system for the case of a weak periodic driving has been intensively studied during past decade within the context of stochastic resonance. We had demonstrated, that for the case of predominantly suprathreshold driving the noise in the output signal is strongly suppressed at certain frequency range: the signal-to-noise ratio demonstrates resonant behavior as function of frequency.

The switching dynamics of an overdamped brownian particle in a "quartic" potential has been intensively studied in the past decade in the frame of stochastic resonance (SR) phenomenon [1]. Stochastic resonance is a nonlinear noise-mediated cooperative phenomenon wherein the coherent response to a deterministic signal can be enhanced in the presence of an optimal amount of noise. It had been observed in a wide variety of electronic systems, such as, e.g., lasers [2], Schmitt triggers [3], tunnel diodes [4] and SQUIDs [5], [6]. It is known, that for a singlelevel threshold systems SR has been observed for the case of weak (underthreshold) driving [1] (although residual SR effects are known to occur for marginally suprathreshold signals [7]). In this case as well as in the case of suprathreshold SR in multilevel threshold systems [8], the manifestation of SR is resonant behavior of signal-to-noise ratio (SNR) or other relevant characteristics as function of noise intensity.

However, most of practical devices are operating in the predominantly suprathreshold regime, when the transition from one state to another one over potential barrier occurs deterministically and noise is the only disturbing factor leading to erroneous switching. As an example of such a situation we can refer to microwave hysteretic SQUID [9], [10], whose dynamics is described by the model of Brownian motion in bistable potential subjected to strong periodic driving at the given frequency. Such SQUID represents a clear example of the device, by its very basic idea operating in strongly suprathreshold regime (its important characteristic is a function of amplitude of output signal versus the amplitude of input driving) and for which presence of noise leads to earlier transitions over potential barrier that results in error of the measured dc magnetic flux. For microwave hysteretic SQUID long standing problem is known: at which parameters it should operate in order to demonstrate maximal sensitivity. On one hand it is known, that with increase of pumping frequency the sensitivity of the SQUID should improve, on the other hand it is known that at frequencies higher than the cut-off frequency, the performance of the device should degrade. Some qualitative treatment of this problem has been done in the past [9], [11], but the question is still opened.

Few papers, where the case of strong periodic driving was considered both in classical [12], [13] and quantum systems [14], were addressed to investigation of area of hysteretic loop and its resonant behavior as function of frequency of driving signal was demonstrated. But, to our knowledge, the investigation of signal-to-noise ratio as function of frequency was not performed for the case of strongly suprathreshold driving. This may be explained by the fact, that the most studies were restricted by adiabatic approximation, where frequency dependence of SNR could not be investigated in detail or by linear response theory, where the driving amplitude was supposed to be small. Nevertheless, in the frame of linear response theory some weak resonant frequency dependence of signal-to-noise ratio was recently observed for a particular case of piecewise rectangular potential [15].

Recently we have shown using description via temporal characteristics, that in a dynamical system with noise subjected to a strong periodic driving, significant suppression of noise is possible in a certain frequency range [16].

The aim of the present paper is to consider fluctuational dynamics of a Brownian particle in a "quartic" potential, study the signal-to-noise ratio and demonstrate that for the case of a strong (suprathreshold) periodic driving the SNR has resonant behavior as function of frequency.

Consider a process of Brownian diffusion in a potential profile

$$U(x, t) = bx^4 - ax^2 + xA \sin(\Omega t + \varphi), \quad (1)$$

where φ is initial phase. It is known that the probability density $W(x, t)$ of the Brownian particle in the overdamped limit (Markov process) satisfies the Fokker-Planck equation (FPE)

$$\frac{\partial W(x, t)}{\partial t} = -\frac{\partial G(x, t)}{\partial x} = \frac{1}{B} \left\{ \frac{\partial}{\partial x} \left[\frac{du(x, t)}{dx} W(x, t) \right] + \frac{\partial^2 W(x, t)}{\partial x^2} \right\}. \quad (2)$$

Here $G(x, t)$ is the probability current, $B = h/kT$, h is the viscosity (in computer simulations we put $h = 1$), T is the temperature, k is the Boltzmann constant and $u(x, t) = U(x, t)/kT$ is the dimensionless potential profile. The initial and the boundary conditions have the following form:

$$W(x, 0) = \delta(x - x_0), G(\pm\infty, t) = 0. \quad (3)$$

In computer simulations we had chosen the following parameters of the potential: $b = 1$, $a = 2$. With such a choice the coordinates of minima equal $x_{min} = \pm 1$, the barrier height $\Delta U = 1$, the critical amplitude A_c is around 1.5 and we have chosen $A = 2$ to be far enough from A_c . We note, that this is not the case "just above the threshold level", considered in [7], but indeed strong driving: the amplitude $A = 2$ is far above the dynamic threshold. We also performed the analysis for $A = 3; 4; 5$: the results are qualitatively the same, only SNR rises accordingly.

The quantity of our interest is the SNR . In accordance with [1] we denote SNR as:

$$SNR = \frac{1}{S_N(\Omega)} \lim_{\Delta\omega \rightarrow 0} \int_{\Omega - \Delta\omega}^{\Omega + \Delta\omega} S(\omega) d\omega, \quad (4)$$

where

$$S(\omega) = \int_{-\infty}^{+\infty} e^{-i\omega\tau} K[\tau] d\tau \quad (5)$$

is the spectral density, $S_N(\Omega)$ is noisy pedestal at the driving frequency Ω and $K[\tau]$ is the correlation function:

$$K[\tau] = \langle \langle x(t + \tau)x(t) \rangle \rangle, \quad (6)$$

where the inner brackets denote the ensemble average and outer brackets indicate the average over initial phase φ .

In order to obtain the correlation function $K[\tau]$ we solved the Eq. (2) numerically, using the Crank-Nicholson scheme.

In Fig. 1 the spectral density $S(\omega)$ is presented for $kT = 0.1$ (the delta-spikes at 1-st and some higher harmonics are out of figure in order to enhance the noise part). One can see that the form of $S(\omega)$ significantly depends on driving frequency Ω , while the amplitude of the output signal is monotonically decreasing function of Ω . In order to study the resonant behavior of spectral density, let us plot the SNR as function of driving frequency Ω . From Fig. 2 one can see, that SNR as function of Ω has strongly pronounced maximum. The location of this maximum at $\Omega = \Omega_{max}$ approximately corresponds to the time scale matching condition: $\Omega_{max} \approx \pi/\tau_{min}$, where τ_{min} is the minimal transition time from one state to another one. The existence of optimal driving frequency may be explained in the following way. Let us consider the case of adiabatically slow driving. If noise is absent, the escape would occur only after the corresponding potential barrier would disappear. If we add some small amount of noise, the escape would occur earlier than in the deterministic case at some nonzero barrier height. If the driving frequency is increased, the potential barrier height will decrease faster and the escape will occur at lower barrier, that is more close to the deterministic case. In the case, when the driving frequency is higher than the cut-off frequency of the system, $\Omega \geq \Omega_c$ (where Ω_c has a dynamical sense: for a given amplitude of the signal the performance of the system significantly degrades above certain frequency), the particle would never escape over potential barrier in the absence of noise and will remain in the vicinity of initial potential minimum, since there is not enough time to reach the basin of attraction of another state. Therefore, there is some frequency range, where at the given small noise intensity the escape will occur over the smallest potential barrier and namely in this case noise has minimal effect on the system that results to the maximal SNR .

In the case when the driving frequency is higher than the cut-off frequency, $\Omega \geq \Omega_c$, adding some amount of noise will help the particle to move to another state and the conventional stochastic resonance may be observed (see the inset of Fig. 2 for $\Omega = 1$). Let us note, that we were not able to observe such intuitively obvious thing as increase of SNR for $kT \rightarrow 0$ in the case $\Omega \geq \Omega_c$ (in this case for $kT = 0$ we will have small but nonzero oscillations near the initial potential minimum) due to divergence of the algorithm for $kT < 0.02$ ($\Omega = 1$) and the last three points, presented in the inset of Fig. 2, correspond to $kT = 0.1; 0.05; 0.02$, respectively.

In conclusion we have shown that in the dynamical system with noise driven by a strong sinusoidal signal (predominantly suprathreshold driving) the influence of noise is significantly reduced in a certain frequency range: the signal-to-noise ratio is a resonant function of frequency of the driving signal. This effect is of real importance for applications since it may allow to operate a concrete device (like a SQUID or other electronic devices) in the regime of minimal noise-induced error.

For driving frequencies higher than the cut-off frequency the conventional (but suprathreshold) stochastic resonance has been observed.

Author wishes to thank Prof. M. Salerno for helpful discussions. This work has been supported by the MURST (Ministero dell'Universita' e della Ricerca Scientifica e Tecnologica), by the INFM (Istituto Nazionale di Fisica della

- [1] for a review on stochastic resonance see L. Gammaitoni, P. Hanggi, P. Jung and F. Marchesoni Rev. Mod. Phys., v. 70, p. 223 (1998) and references therein.
- [2] B. McNamara, B., K. Wiesenfeld, and R. Roy, Phys. Rev. Lett. v. 60, p. 2626 (1988).
- [3] S. Fauve, and F. Heslot, Phys. Lett. A, v. 97, p. 5 (1983).
- [4] R. N. Mantegna, and B. Spagnolo, Phys. Rev. E v. 49, p. R1792 (1994).
- [5] A. D. Hibbs, A. L. Singsaas, E. W. Jacobs, A. R. Bulsara, J. J. Bekkedahl, and F. Moss, J. Appl. Phys. v. 77, p. 2582 (1995).
- [6] R. Rouse, S. Han, and J. E. Lukens, Appl. Phys. Lett. v. 66, p. 108 (1995).
- [7] F. Apostolico, L. Gammaitoni, F. Marchesoni, and S. Santucci, Phys. Rev. E v. 55, p. 36 (1997).
- [8] N. G. Stocks, Phys. Rev. Lett., v. 84, p. 2310 (2000).
- [9] K.K. Likharev, *Dynamics of Josephson Junctions and Circuits*, (Gordon and Breach, New York), 1986.
- [10] D. Koelle, R. Kleiner, F. Ludwig, E. Dantsker and John Clarke, Rev. Mod. Phys., v. 71, p. 631 (1999).
- [11] R. A. Burhman and L. D. Jackel, IEEE Trans. Magn., v. MAG-13, p. 879 (1977).
- [12] M. C. Mahato and S. R. Shenoy, Phys. Rev. E, v. 50, p. 2503 (1994).
- [13] J. C. Phillips and K. Schulten, Phys. Rev. E, v. 52, p. 2473 (1995).
- [14] M. Thorwart and P. Jung, Phys. Rev. Lett., v. 78, p. 2503 (1997).
- [15] V. Berdichevsky and M. Gitterman, J. Phys. A: Math. Gen., v. 29, p. L447 (1996).
- [16] A. L. Pankratov and M. Salerno, Phys. Lett. A, v. 273, p. 162 (2000).




FIG. 1. Spectral density $S(\omega)$ with enhanced noise part, $kT = 0.1$, $A = 2$.




FIG. 2. Signal-to-noise ratio as function of driving frequency for $A = 2$. Inset: SNR as function of kT for $\Omega = 1$.